

## Bluetooth® Printer Adapter



The BT200 Bluetooth® Printer Adapter, is a quick and effective solution for upgrading parallel port printers into Bluetooth® wireless printers. The BT200 is easy to install, allowing users to carry out a full installation without the need to reinstall the printer drivers.

By replacing the printer parallel cable the BT200 enables easy wireless printing from any Bluetooth® enabled device such as a desktop, laptop or PDA.

**FieldSoftware PrintPocketCE™ trial version for PocketPC 2002/2000 PDAs is contained inside the BT200 Utility CD !**

Note: Extra printing software is required with Bluetooth enabled PDA, the exact version varying according to the PDA's OS



BT200 retail box

### General Radio

Carrier Frequency: 2.400-2.480 GHz

### Spread Spectrum

FHSS (Frequency Hopping Spread Spectrum)

### Cover Range

10 meters (33 feet) - Class II, radius from device in typical use (varies with building construction)

### Radio Performance – Receiver

Rx sensitivity: Typical -80dBm

### Bluetooth Profile Support

Bluetooth v1.1 - Serial Port Profile(SPP Profile)

### Printing Speed

Up to 115200bps

### Connection

36-pin Parallel Port Connector

### Hardware

CPU: ATMEL 89S52.  
Buffer Memory: 32K Bytes SRAM  
Supply Voltage: 6V  
Antenna: Chip Antenna  
LED Indicator: 1 LED-Data receiving / Power status

### Environment

Operating Temperature: 0°C ~ +55°C  
Storage Temperature: -10°C ~ +85°C

### System Support

Windows XP / 2000 / ME / 98SE  
PocketPC 2003 / 2002 / 2000

### Dimensions & Weight

WxLxH (including connector): 78.6 x 32 x 20.6 mm  
Gross Weight (without Power Adapter): 52 g

### AC/DC Power Adapter Spec.

- Input: AC +100~240V / 50~60HZ  
- Output: DC +6V / 1A  
- Power Consumption: 0.7W @ 6V DC