
Bluetooth Compact Flash Card Quick Start Guide

NOTE: Read this Quick Start Guide before installing the Bluetooth Compact Flash card. For complete safety precautions and configuration details, please read the Bluetooth Compact Flash card User's Guide.

PACKAGE CONTENTS

Item	Location
Bluetooth Compact Flash Card (Class 2)	In box
Bluetooth Compact Flash Card Quick Start Guide	In box
Bluetooth Compact Flash Card CD-ROM	In box
Bluetooth Application Software	On CD
Bluetooth Compact Flash Card User's Guide	On CD

If any item is missing, please contact your product provider.

PRODUCT INTRODUCTION

The Bluetooth CF card allows a PDA with a compact flash port to communicate with other devices with Bluetooth technology. When used with the Bluetooth application software, it can perform wireless network applications such as information exchange, file transfer, network access, dial-up networking, and more.

SYSTEM REQUIREMENTS

A desktop computer with:

Microsoft Windows 98SE, Me, 2000 or XP operating system

CD-ROM drive

Microsoft ActiveSync, version 3.5 or greater

A handheld computer capable of accepting a Compact Flash card

Your Bluetooth Compact Flash Card (this software may not work with other brands' Bluetooth compact flash cards; please consult your vendor for details)

INSTALLATION OF THE BLUETOOTH APPLICATION SOFTWARE

1. Insert the Bluetooth Compact Flash card into the handheld device and

connect it to the desktop computer. Microsoft ActiveSync will automatically establish a connection.

2. On the desktop computer:
 - a) Insert the BTW-CE compact disc into the CD-ROM drive.
 - b) When the Welcome screen appears, Click Next to continue.
 - c) Click Yes to accept the License Agreement and install the software on the desktop computer.

NOTE: If the connection between the handheld and the desktop computers is not open, an error message appears: "On the next PDA connection, the installed applications will be downloaded to the device." Installation will resume when ActiveSync detects a connection to the handheld device

3. On the handheld device: tap Yes to accept the default directory and install the software.
4. On the desktop computer: Click OK to close the Download Complete dialog box, and then click Finish.
5. On the handheld device:
 - a) A welcome screen will be shown with basic instructions to use BTW-CE.
 - b) Check off **ADD a shortcut in the Start menu** in order to have access to the **Bluetooth Manager** from the Start menu (otherwise, the **Bluetooth Manager** will be accessible from **Start > Programs**).
 - c) Perform a "soft" reset of the handheld computer. Refer to your device's documentation for the exact procedure.

NOTE: A soft reset leaves installed applications and stored data intact.

A hard reset deletes ALL downloaded applications on the handheld.

See the handheld computer's documentation for additional information.


Uninstall a prior version of BTW-CE

1. Connect the handheld computer, via its cradle and Microsoft ActiveSync, to the desktop computer.
2. On the desktop computer, in the system tray, double-click the ActiveSync icon.
3. From the ActiveSync Tools menu, click Add/Remove Programs...
4. In the list of applications installed on the handheld computer, clear (un-check) WIDCOMM BTWCE. Verify that WIDCOMM BTWCE is still highlighted

5. Click the Remove button
6. Click OK to acknowledge the Remove Application notification.

The prior version of BTW-CE will be uninstalled on both the handheld and desktop computers (follow any additional on-screen instructions that may appear on the desktop computer to complete the uninstall process).

Bluetooth Control Panel: Configuring BTW-CE

1. BTW-CE provides a Control Panel to adjust Bluetooth settings.
2. To access the Control Panel, in the lower-right corner of the Today screen, tap the Bluetooth icon .
3. BTW-CE can have multiple saved configurations. Individual configuration sets are saved in profiles, which can be quickly loaded to meet the appropriate situation.
4. The Control Panel has seven tabs. All tabs are not visible on the screen at the same time; use the arrows to the right of the tab names to scroll back-and-forth and expose the different tabs.

The Control Panel's tabs are:

- General
 - User profile selection
 - Bluetooth status (ON/OFF) indicator
 - Hardware power control (ON/OFF)
 - Shortcut to the Bluetooth Manager
- Accessibility
 - Set the device name
 - The device's Bluetooth Device Address (BDA)
 - Determine which remote devices are allowed to connect
 - Determine whether remote devices can "see" this Pocket PC
- Service tabs—BTW-CE can provide four services. They are:
 - File Transfer—set the highest-level directory on this Pocket PC that remote devices will be able to access
 - Information Exchange—Set the default business card (Pocket Outlook contact entry)
 - Serial Port—Bluetooth serial port information
 - Dial-up Networking—configure the COM port, baud rate and flow control



- About—there are no configurable options on this tab.
 - Software version information
 - Copyright information
 - Website and Technical Support links
 -

Bluetooth Manager: Using BTW-CE

To access the Bluetooth Manager:

From the Today screen, tap  > Programs > Bluetooth Manager.

The Bluetooth Manager has

- Two tabs:
 - My shortcuts—displays shortcuts and establishes connections
 - Active Connections—displays active incoming and outgoing connections
- Three menus:
 - New
 - Connect!—create a new connection shortcut using the Bluetooth Connection Wizard
 - Tools
 - Paired devices—pair/un-pair with other devices
 - Business Card Exchange—open the Business Card Exchange
 - View—controls the on-screen display (icons or list).
- Two icons:
 -  Accesses the Bluetooth Connection Wizard, which helps you setup connections with remote Bluetooth devices. This icon is a shortcut to the New > Connect! menu item.
 -  Accesses the Bluetooth Business Card Exchange screen. This icon is a shortcut to the Tools > Business Card Exchange menu item. It allows you to:
 - Get a business card from a remote device
 - Send your business card to a remote device
 - Exchange business cards with a remote Bluetooth device.

75-143200-01 V1.1